

## Isolated Measurement Systems

### TIVM1, TIVM1L, TIVH08, TIVH08L, TIVH05, TIVH05L, TIVH02, TIVH02L Datasheet



The Tektronix TIVM and TIVH Series IsoVu™ Measurement Systems offer galvanically isolated measurement solutions for accurately resolving high bandwidth, differential signals up to  $\pm 2500$  V in the presence of large common mode voltages with the best in class common mode rejection performance across its bandwidth.

#### Features and benefits

- Bandwidths from DC to 1 GHz
- 100 Million to 1 (160 dB) Common Mode Rejection from DC up to 1 MHz
- 10,000 to 1 (80 dB) Common Mode Rejection at 1 GHz
- 60 kV peak Common Mode Voltage
- Up to  $\pm 2500$  V Differential (DC + pk AC)
- Up to  $\pm 2500$  V offset range
- Output clamping
- Safety certified
- DC and AC input coupling

#### Applications

- Half/Full Bridge designs using GaN, SiC, IGBTs
- Floating measurements
- Power Converter design
- Power Device evaluation
- Switching Power Supply design
- Inverter design
- Motor Drive design
- Electronic Ballast design
- EMI
- ESD
- Current shunt measurements
- Remote probing capability

#### Product Description

The TIVM and TIVH Series (IsoVu) products can be used on most Tektronix oscilloscopes with the TekVPI interface and on MSO/DPO70K series oscilloscopes with the TCA-VPI50 adapter. IsoVu utilizes an electro-optic sensor that converts the electrical signal from the sensor tip cables to an optical signal, which electrically isolates the device-under-test from the oscilloscope. IsoVu incorporates four separate lasers, an optical sensor, five optical fibers, and sophisticated feedback and control techniques. The sensor head, which connects to the test point, has complete electrical isolation and is powered over one of the optical fibers (No batteries required). IsoVu is an ideal solution for users making the following measurements:

- Differential measurements in the following conditions:
  - Complete galvanic isolation is required
  - High common mode voltage
  - High frequency common mode interference
  - High frequency measurements
- Measurements in high EMI environments
- EMI compliance testing
- ESD testing

## Specifications

All specifications are guaranteed unless noted otherwise. All specifications apply to all models unless noted otherwise.

### Overview

#### Overview

Characteristic	TIVM1/TIVM1L	TIVH08/TIVH08L	TIVH05/TIVH05L	TIVH02/TIVH02L
Bandwidth/Rise time (Typical)	1 GHz / $\leq$ 350 ps	800 MHz / $\leq$ 435 ps <sup>1</sup>	500 MHz / $\leq$ 700 ps	200 MHz / $\leq$ 1.8 ns
Fiber cable length	TIVM1: 3 m (9.8 ft) TIVM1L: 10 m (32.8 ft)	TIVH08: 3 m (9.8 ft) TIVH08L: 10 m (32.8 ft)	TIVH05: 3 m (9.8 ft) TIVH05L: 10 m (32.8 ft)	TIVH02: 3 m (9.8 ft) TIVH02L: 10 m (32.8 ft)

### Attenuation and ranges TIVM Series

TIVM Series attenuation, Differential input voltage range, Offset range, Single-ended impedance (Typical) *Use only the sensor tip cables listed below with the TIVM Series.*

Sensor tip cable	Attenuation	Differential input voltage		Offset range	Single-ended input impedance
		1X range	2X range		
SMA input	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 2$ V	50 $\Omega$    N.A.
<b>MMCX sensor tip cables</b>					
IVTIP1X	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 2$ V	50 $\Omega$    N.A.
IVTIP5X	5X	$\pm 2.5$ V	$\pm 5$ V	$\pm 10$ V	250 $\Omega$    $< 1$ pF
IVTIP10X	10X	$\pm 5$ V	$\pm 10$ V	$\pm 20$ V	500 $\Omega$    $< 1$ pF
IVTIP25X	25X	$\pm 12.5$ V	$\pm 25$ V	$\pm 50$ V	1.25 k $\Omega$    $< 1$ pF
IVTIP50X	50X	$\pm 25$ V	$\pm 50$ V	$\pm 100$ V	2.5 k $\Omega$    $< 1$ pF

### Attenuation and ranges TIVH Series

TIVH Series attenuation, Differential input voltage range, Offset range, Single-ended impedance (Typical) *Use only the sensor tip cables listed below with the TIVH Series.*

Sensor tip cable	Attenuation	Differential input voltage		Offset range	Single-ended input impedance
		1X range	2X range		
SMA input	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 25$ V	1 M $\Omega$    20 pF
<b>MMCX sensor tip cables</b>					
IVTIP1X	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 25$ V	1 M $\Omega$    35 pF <sup>2</sup>
MMCX10X	10X	$\pm 5$ V	$\pm 10$ V	$\pm 250$ V	10 M $\Omega$    6 pF
MMCX50X	50X	$\pm 25$ V	$\pm 50$ V	$\pm 250$ V	10 M $\Omega$    3 pF
MMCX250X	250X	$\pm 125$ V	$\pm 250$ V	$\pm 250$ V	10 M $\Omega$    2 pF
<b>0.100 in Pitch (2.54 mm) Square Pin sensor tip cables</b>					
SQPIN100X	100X	$\pm 50$ V	$\pm 100$ V	$\pm 600$ V	10 M $\Omega$    3.5 pF

Table continued...

<sup>1</sup> The 800 MHz bandwidth is achieved with the 50X and greater attenuation tips (MMCX50X, MMCX250X, SQPIN100X, SQPIN500X, WSQPIN1000X, or WSQPIN2500X).

Sensor tip cable	Attenuation	Differential input voltage		Offset range	Single-ended input impedance
		1X range	2X range		
SQPIN500X	500X	±250 V	±500 V	±600 V	10 MΩ    3.5 pF
<b>0.200 in Pitch (5.08 mm) Square Pin sensor tip cables</b>					
WSQPIN1000X	1000X	±500 V	±1000 V	±2500 V	40 MΩ    3.5 pF
WSQPIN2500X	2500X	±1250 V	±2500 V	±2500 V	40 MΩ    3.5 pF

## Common mode rejection ratio TIVM Series

TIVM Series Common mode rejection ratio, sensor tip cables, and adapters (Typical)

Sensor tip cable/ adapter	DC	1 MHz	100 MHz	200 MHz	500 MHz	1 GHz
<b>MMCX Sensor tip cables</b>						
IVTIP1X	160 dB	124 dB	120 dB	110 dB	100 dB	90 dB
IVTIP5X	160 dB	124 dB	120 dB	110 dB	100 dB	90 dB
IVTIP10X	160 dB	124 dB	120 dB	110 dB	100 dB	90 dB
IVTIP25X	160 dB	120 dB	110 dB	100 dB	100 dB	90 dB
IVTIP50X	160 dB	116 dB	100 dB	90 dB	90 dB	80 dB
<b>Adapters</b>						
MMCX-to 0.1 in (2.54 mm)	160 dB	100 dB	70 dB	60 dB	40 dB	30 dB
MMCX-to 0.062 in (1.57 mm)	160 dB	100 dB	70 dB	60 dB	40 dB	30 dB

## Common mode rejection ratio TIVH series

TIVH Series Common mode rejection ratio, sensor tip cables, and adapters (Typical)

Sensor tip cable/ adapter	DC	1 MHz	100 MHz	200 MHz	500 MHz	800 MHz
<b>MMCX Sensor tip cables</b>						
IVTIP1X	160 dB	120 dB	120 dB	110 dB	110 dB	110 dB
MMCX10X	160 dB	120 dB	110 dB	102 dB	91 dB	85 dB
MMCX50X	160 dB	116 dB	100 dB	93 dB	85 dB	80 dB
MMCX250X	160 dB	104 dB	85 dB	80 dB	73 dB	70 dB
<b>0.100 in Pitch (2.54 mm) Square Pin sensor tip cables</b>						
SQPIN100X	160 dB	110 dB	60 dB	50 dB	37 dB	30 dB
SQPIN500X	160 dB	100 dB	70 dB	57 dB	39 dB	30 dB
<b>0.200 in Pitch (5.08 mm) Square Pin sensor tip cables</b>						
Table continued...						

<sup>2</sup> With 6-inch tip cable sensor head 20 pF plus cable 15 pF.

Sensor tip cable/ adapter	DC	1 MHz	100 MHz	200 MHz	500 MHz	800 MHz
WSQPIN100 0X	160 dB	100 dB	60 dB	47 dB	29 dB	20 dB
WSQPIN250 0X	160 dB	100 dB	60 dB	48 dB	33 dB	25 dB
<b>Adapters</b>						
MMCX-to 0.1 in (2.54 mm)	160 dB	85 dB	70 dB	60 dB	40 dB	30 dB
MMCX-to 0.062 in (1.57 mm)	160 dB	85 dB	70 dB	60 dB	40 dB	30 dB

### Maximum non-destructive voltage TIVM Series

TIVM Series Maximum non-destructive voltage (Typical)

Sensor tip cable	V <sub>pk</sub> (DC + peak AC)	V <sub>RMS</sub>
Sensor head only	4.3 V <sub>pk</sub>	3 V <sub>RMS</sub>
IVTIP1X	4.3 V <sub>pk</sub>	3 V <sub>RMS</sub>
IVTIP5X	21.5 V <sub>pk</sub>	12 V <sub>RMS</sub>
IVTIP10X	43 V <sub>pk</sub>	16 V <sub>RMS</sub>
IVTIP25X	107.5 V <sub>pk</sub>	25 V <sub>RMS</sub>
IVTIP50X	200 V <sub>pk</sub>	35 V <sub>RMS</sub>

### Maximum non-destructive voltage TIVH Series

TIVH Series Maximum non-destructive voltage (Typical)

Sensor tip cable	V <sub>pk</sub> (DC + peak AC) <sup>3</sup>
Sensor head only	25 V <sub>pk</sub>
IVTIP1X	25 V <sub>pk</sub>
MMCX10X	250 V <sub>pk</sub>
MMCX50X	250 V <sub>pk</sub>
MMCX250X	250 V <sub>pk</sub>
SQPIN100X	600 V <sub>pk</sub>
SQPIN500X	600 V <sub>pk</sub>
WSQPIN1000X	2500 V <sub>pk</sub>
WSQPIN2500X	2500 V <sub>pk</sub>

<sup>3</sup> Derated with frequency; refer to the Maximum differential input voltage vs. frequency derating graph in the Specifications section of the TIVH Series IsoVu Measurement System User Manual.

## Common mode voltage

Common mode voltage 60 kV peak

## Common mode input impedance

Common mode input impedance (Typical)

Input resistance Galvanically isolated through the fiber optic connection  
 Input capacitance <sup>4</sup> < 2 pF

## DC Gain accuracy

DC Gain accuracy

Differential DC gain accuracy in 1X range  $\pm 3\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error

Differential DC gain accuracy in 2X range 60% of  $\pm$  Full Scale:  $\pm 3\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error >60% to 80% of  $\pm$  Full Scale: 0% to  $-4\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error

>80% to 100% of  $\pm$  Full Scale: 0% to  $-7\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error

## System noise

System noise (input referred)  
(Typical)

Sensor tip cable/adaptor	1X Range	2X Range
TIVH08/TIVH08L Sensor head input SMA	< 1.2 mV <sub>rms</sub>	< 1.4 mV <sub>rms</sub>
TIVH05/TIVH05L Sensor head input SMA	< 0.72 mV <sub>rms</sub>	< 0.85 mV <sub>rms</sub>
TIVH02/TIVH02L Sensor head input SMA	< 0.61 mV <sub>rms</sub>	< 0.75 mV <sub>rms</sub>
TIVM1/TIVM1L Sensor head input SMA	< 0.8 mV <sub>rms</sub>	< 1.6 mV <sub>rms</sub>
Input referred noise with tip cable	(Sensor head input SMA noise) * (Tip cable attenuation)	(Sensor head input SMA noise) * (Tip cable attenuation)
Examples:	TIVH08 1X Range with MMCX10X tip cable: Noise = (1.2 mV <sub>rms</sub> ) * (10) = 12 mV <sub>rms</sub>	TIVH08 2X Range with MMCX10X tip cable: Noise = (1.4 mV <sub>rms</sub> ) * (10) = 14 mV <sub>rms</sub>

## Propagation delay

Propagation delay

3 meter fiber cable 35 ns  $\pm$ 5 ns  
 10 meter fiber cable 68 ns  $\pm$ 7 ns

## Laser certification

Laser certification CLASS I LASER PRODUCT

<sup>4</sup> The capacitance between the sensor head and a reference plane. The sensor head is placed six inches (15.25 cm) above the reference plane.

This product complies with 21 CFR 1040.10 and 1040.11 except for deviations pursuant to Laser Notice No. 50, dated June 24, 2007.

## Ordering information

### Models

#### TIVM models

TIVM1	Tektronix IsoVu 1 GHz Medium Voltage with 3 m cable
TIVM1L	Tektronix IsoVu 1 GHz Medium Voltage with 10 m cable

#### TIVH models

TIVH08	Tektronix IsoVu 800 MHz High Voltage with 3 m cable
TIVH08L	Tektronix IsoVu 800 MHz High Voltage with 10 m cable
TIVH05	Tektronix IsoVu 500 MHz High Voltage with 3 m cable
TIVH05L	Tektronix IsoVu 500 MHz High Voltage with 10 m cable
TIVH02	Tektronix IsoVu 200 MHz High Voltage with 3 m cable
TIVH02L	Tektronix IsoVu 200 MHz High Voltage with 10 m cable

### TIVM series

#### Standard accessories

016-2108-xx	IsoVu product carrying case, soft case
016-2110-xx	IsoVu accessories carrying case, soft case
003-1946-xx	Solder aid for 0.062-inch (1.57 mm) pitch square pins (0.016 - 0.018-inch (0.4 - 0.46 mm) square pin installation tool)
IVTIP5X	5X Sensor tip cable
IVTIP25X	25X Sensor tip cable
003-1947-xx	5/16-inch SMA wrench/driver tool
131-9717-xx	Probe tip adapter (blue), MMCX to 0.1-inch (2.54 mm) square pin (0.025-inch (0.635 mm) square pins)
131-9677-xx	Probe tip adapter (white), MMCX to 0.062-inch (1.57 mm) square pin (0.016 - 0.018-inch (0.4 - 0.46 mm) square pins)
020-3169-xx	DUT Interface pin kit with (qty. 20) 0.018-inch (0.46 mm) round solder-in pins
352-1171-xx	Flexible tripod with quick release
344-0693-xx	Flexible tripod feet, 3 each
352-1170-xx	Probe tip tripod support with living hinge, 2 each
071-3495-xx	User manual (English)
---	Certificate of traceable calibration

Translated manuals can be downloaded as pdf files on your local Tektronix Web site.

#### Recommended accessories

IVTIP1X	1X Sensor tip cable
IVTIP10X	10X Sensor tip cable

IVTIP50X 50X Sensor tip cable

## TIVH series

### Standard accessories

016-2135-xx	IsoVu product carrying case, soft case
016-2134-xx	IsoVu accessories carrying case, soft case
MMCX50X	50X Sensor tip cable
SQPIN500X	500X Sensor tip cable
003-1951-xx	5/16-inch SMA wrench/driver tool
131-9717-xx	Probe tip adapter (blue), MMCX to 0.1-inch (2.54 mm) square pin (0.025-inch (0.635 mm) square pins)
352-1171-xx	Flexible tripod with quick release
344-0693-xx	Flexible tripod feet, 3 each
352-1170-xx	Probe tip tripod support with living hinge, 2 each
071-3556-xx	User manual (English)
—	Certificate of traceable calibration

Translated manuals can be downloaded as pdf files on your local Tektronix Web site.

### Recommended accessories

003-1946-xx	Solder aid for 0.062-inch (1.57 mm) pitch square pins (0.016 - 0.018-inch (0.4 - 0.46 mm) square pin installation tool)
131-9677-xx	Probe tip adapter (white), MMCX to 0.062-inch (1.57 mm) square pin (0.016 - 0.018-inch (0.4 - 0.46 mm) square pins)
196-3546-xx	MMCX to IC grabber lead
196-3547-xx	Square pin header to IC grabber lead
020-3169-xx	DUT Interface pin kit with (qty. 20) 0.018-inch (0.46 mm) round solder-in pins
IVTIP1X	1X Sensor tip cable
MMCX10X	10X Sensor tip cable
MMCX250X	250X Sensor tip cable
SQPIN100X	100X Sensor tip cable
WSQPIN1000X	1000X Sensor tip cable
WSQPIN2500X	2500X Sensor tip cable

## Supported oscilloscopes

The measurement systems can be used with the following Tektronix oscilloscopes. For oscilloscopes not included in this list, contact your local Tektronix representative.

- 5 Series MSO (WSQPIN2500X tip cables require V1.6 or later oscilloscope firmware)
- MDO3000 series (WSQPIN tip cables require V1.26 or later oscilloscope firmware)
- MDO4000C series (WSQPIN tip cables require V1.06 or later oscilloscope firmware)
- MSO/DPO/MDO4000B series (WSQPIN tip cables are not compatible)

- MSO/DPO5000B series
- DPO7000C series

In addition to the above oscilloscopes, the TIVH and TIVM measurement systems can also be used with the following oscilloscopes with a TCA-VPI50 adapter.

- MSO/DPO70000C series
- MSO/DPO70000DX series
- DPO70000SX series

## Options

### Service options

Opt. C3	Calibration Service 3 Years
Opt. C5	Calibration Service 5 Years
Opt. D1	Calibration Data Report
Opt. D3	Calibration Data Report 3 Years (with Opt. C3)
Opt. D5	Calibration Data Report 5 Years (with Opt. C5)
Opt. G3	Complete Care 3 Years (includes loaner, scheduled calibration, and more)
Opt. R3	Repair Service 3 Years (including warranty)
Opt. R5	Repair Service 5 Years (including warranty)

Probes and accessories are not covered by the oscilloscope warranty and Service Offerings. Refer to the datasheet of each probe and accessory model for its unique warranty and calibration terms.

ASEAN / Australasia (65) 6356 3900  
 Belgium 00800 2255 4835\*  
 Central East Europe and the Baltics +41 52 675 3777  
 Finland +41 52 675 3777  
 Hong Kong 400 820 5835  
 Japan 81 (120) 441 046  
 Middle East, Asia, and North Africa +41 52 675 3777  
 People's Republic of China 400 820 5835  
 Republic of Korea +822 6917 5084, 822 6917 5080  
 Spain 00800 2255 4835\*  
 Taiwan 886 (2) 2656 6688

Austria 00800 2255 4835\*  
 Brazil +55 (11) 3759 7627  
 Central Europe & Greece +41 52 675 3777  
 France 00800 2255 4835\*  
 India 000 800 650 1835  
 Luxembourg +41 52 675 3777  
 The Netherlands 00800 2255 4835\*  
 Poland +41 52 675 3777  
 Russia & CIS +7 (495) 6647564  
 Sweden 00800 2255 4835\*  
 United Kingdom & Ireland 00800 2255 4835\*

Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777  
 Canada 1 800 833 9200  
 Denmark +45 80 88 1401  
 Germany 00800 2255 4835\*  
 Italy 00800 2255 4835\*  
 Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90  
 Norway 800 16098  
 Portugal 80 08 12370  
 South Africa +41 52 675 3777  
 Switzerland 00800 2255 4835\*  
 USA 1 800 833 9200

\* European toll-free number. If not accessible, call: +41 52 675 3777

**For Further Information.** Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit [www.tek.com](http://www.tek.com).

Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.